











Built with reliability in mind, the MFC-L2710DN, is a printer of choice for many busy home and small offices. This multifunction device, offers print, copy, scan and fax, in a compact, desktop friendly unit. Combined with high speed and low noise printing - you can be setup and running in minutes.



# **Key Features:**

- Fast print speeds of up to 30 pages per minute
- Automatic 2-sided print
- 250 sheet paper input
- 50 sheet Auto Document Feeder
- Wired connectivity
- Up to 700 Page\* inbox toner
- 64MB memory

# Performance designed for businesses of tomorrow

Designed to be set-up and ready to be used in minutes. The MFC-L2710DN provides fast print speeds of up to 30 pages per minute, and a 50 sheet automatic document feeder, enabling you to copy and scan multi-page documents. Together, with the option of scanning and saving directly to SharePoint and other destinations.

# Maximum value for money

The feature rich, MFC-L2710DN, is easily networked into your busy home or small office. With built-in automatic 2-sided printing, large paper tray and a choice of toners, you can spend more time focusing on what matters to you.

# **Quiet without compromise**

Print quietly without comprising on speed or quality, operating at the lowest decibel in class (under 50dB). You can now focus on the work you need to, without interruption.

# Designed to go the distance

Built to perform for longer. The MFC-L2710DN, has been designed with you in mind. Made from robust and hardwearing materials and supported by outstanding service as standard, providing the peace of mind that your printer will keep on going.



#### General

**Technology** Electrophotographi c Laser Printer

**Laser Classification** Class 1 Laser

Product (IEC60825-1:2014)

**Processor** 600MHz

Memory 64MB

**Wired Network Interface** 10Base-T/100Base-TX

**Control Panel** 2 Line, 16 character LCD Display

**Local Interface** Hi-Speed USB 2.0

## **Print**

Print Speed Standard (A4)

Up to 30ppm (pages per minute)

Print Speed 2-Sided (A4)

Up to 15 sides per minute (7.5 sheets per minute)

Resolution

Up to 1,200 x 1,200dpi

**Automatic 2-Sided Printing** 

Print on to both sides of the paper

**FPOT (First Print Out Time)** 

Less than 8.5 seconds from ready mode

**Warm Up Time** 

Less than 9 seconds from sleep mode

**Print Languages** 

GDI

## **Printer Functions**

N-up Printing<sup>3</sup>

Reduce up to 2, 4, 9, 16 or 25 A4 pages into just one A4 page (Mac, up to 2, 4, 6, 9, or 16)

Watermark Printing<sup>4</sup>

Watermark your documents with predefined text or with your own user-defined messages

**Booklet Printing<sup>4</sup>** 

Print documents in A5 booklet format using automatic or manual 2-sided print

### **Printer Driver**

Windows®

Windows®10 (32 & 64 bit editions) Windows®8 (32 & 64 bit editions) Windows®7 (32 & 64 bit editions) Windows® Server 2016 (32 & 64 bit editions)\* Windows® Server 2012, 2012R2 & 2008R23 Windows® Server 2008

(32 & 64 bit editions)\*

Macintosh<sup>5</sup>

macOS 10.8.x or greater

Linux<sup>5</sup>

CUPS, LPD/LPRng (32 & 64 bit editions)

All specifications correct at the time of printing and are subject to Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of

their respective companies.

<sup>\*</sup> Windows® Server supports network printing

<sup>1</sup> Approx declared yield value in accordance with ISO/IEC 19752.

<sup>2</sup> Calculated with 80g/m² paper.

<sup>3</sup> Windows® & Mac® only.

<sup>4</sup> Windows®only.

<sup>5</sup> Optional download.

<sup>6</sup> Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

<sup>7</sup> Requires Brother software.

# Standard Paper Handling

Paper Input<sup>2</sup>
Standard Tray - 250
sheets Manual feed slot - 1 sheet

Automatic Document Feeder (ADF) – 50 Sheets Paper Output<sup>2</sup>
Face Down - 120
sheets Face Up
(Straight Paper Path) - 1
sheet

## **Media Specification**

Media Types & Weights Standard Plain & recycled paper (between 60 - 163g/m²) Manual feed slot Plain, Recycled, Bond, Label, Envelope, (between 60 - 230g/m²) 2-sided Print Plain & recycled paper (between 60 - 105g/m²) Envelope & Label Printing
Yes, from the Manual feel
slot: support for 1 envelope /
sheet

Media Sizes
Standard Tray
A4, Letter, A5, A5 (Long
Edge), A6, Executive
Manual feed slot
Width: 76.2mm to 215.9mm x
Length: 127mm to 355.6mm
2-sided Print
A4

# Mobile / Web Based Printing & Scanning

Brother iPrint&Scan (Android/ iPad / iPhone / iPod/ Windows® Phone/ 8,10 & RT)

Print from, scan to, preview copies and check the machine status from a mobile/ tablet/ laptop device

Google Cloud Print 2.0 Print most common file types from any Google Cloud Print enabled application

#### **AirPrint**

Print from and scan to most common file types from any AirPrint enabled application

Brother Print Service Plugin Print from Android devices without a dedicated App

### Mopria

Print most common file types from Mopria supported Android devices

## Copy

Speed - (A4) Up to 30cpm (copies per minute)

FCOT (First Copy Time Out) Less than 10 seconds from ready mode

**Resolution**Up to 600 x 600dpi

All specifications correct at the time of printing and are subject to change.
Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of their respective companies.

<sup>1</sup> Approx declared yield value in accordance with ISO/IEC 19752.

<sup>2</sup> Calculated with 80g/m² paper.

<sup>3</sup> Windows® & Mac® only.

<sup>4</sup> Windows®only.

<sup>5</sup> Optional download.

<sup>6</sup> Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

<sup>7</sup> Requires Brother software.

#### Scan

Scanner Type

CIS (Contact Image Sensor)

Colour & Mono Scanning

Scan Speed Mono

23.6ipm (images per minute)

Scan Speed Colour

7.5ipm (images per minute)

Scan Resolution from ADF

Up to 600 x 600dpi

Scan Resolution from

Scanner Glass

Up to 1,200 x 1,200dpi

Interpolated Scan Resolution

Up to 19,200 x 19,200dpi

Standard Functions<sup>7</sup> Scan to E-mail, OCR, Image & File Scan Features

Remove Background, Skip Blank Page<sup>4</sup>, ID Scan<sup>4</sup>,

1 to 2 Scan4, Split PDF

Scan to SharePoint<sup>4&7</sup>

Scan documents directly into SharePoint

Windows® Web Services Scanning

Scan direct into Windows® (from Windows® 7 & onwards) without needing to install a scanner driver

## **Scanner Driver**

Windows® TWAIN & WIA Windows®10 (32 & 64 bit editions)

Windows®8.1 (32 & 64 bit editions) Windows®8

(32 & 64 bit editions)

Macintosh<sup>5</sup>

TWAIN & AirPrint macOS 10.8.x or greater

Linux<sup>5</sup>

SANE(32 & 64 bit editions)

# Fleet Management Tools

BRAdmin Light<sup>485</sup> LAN/WAN management software **Embedded Web Server** 

Web based print management software embedded onto the device

**Driver Deployment Wizard**<sup>4</sup> Easily create print drivers for hassle free deployment over your network

# PrintSmart Solutions (optional)

PrintSmart Cost Control
Monitor and control printing
costs for all Brother and
3rd party devices

For more information on PrintSmart Solutions visit:

## **Address Book**

**Speed Dials** 

200 locations for E-mail addresses and fax numbers

1 Approx declared yield value in accordance with ISO/IEC 19752.

7 Requires Brother software.

All specifications correct at the time of printing and are subject to change. Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of

their respective companies.

<sup>2</sup> Calculated with 80g/m² paper.

<sup>3</sup> Windows® & Mac® only.

<sup>4</sup> Windows®only.

<sup>5</sup> Optional download.

<sup>6</sup> Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

## **Network and Security**

#### Wired Network

Built in Ethernet 10Base- T/100Base-TX

## Network Protocols TCP/IP (IPv4 and IPv6)

Wired Network Security SMTP-AUTH, SNMP v3,SSL/ TLS(SMTP,HTTP,IPP)

#### IPv4

ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, SMTP Client, IPP/IPPS, FTP Server, SNMPv1/v2c/v3, HTTP/HTTPS server, TFTP client and server, ICMP, Web Services (Print), SNTP Client

#### IPv6

NDP, RA, DNS resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, IPP/IPPS, SMTP Client, FTP Server, SNMPv1/v2c/v3, HTTP/ HTTPS server, TFTP client and server, ICMPv6, SNTP Client, Web Services (Print)

#### **E-mail Notifications**

Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing

### **E-mail Reports**

Receive usage reports on a regular basis via e-mail

#### **IP Filter**

Restrict which network users can or cannot access the device over the network (IPv4 only)

#### **Setting Lock**

Secures access to the devices control panel by locking it

## **Supplies**

# Inbox Toner 700 pages<sup>1</sup>

**Standard Yield Toner** 1,200 pages<sup>1</sup> (TN-2410)

**High Yield Toner** 3,000 pages<sup>1</sup>(TN-2420)

Drum (DR-2400) Approx 12,000 pages

## **Carton Contents**

Toner cartridge, drum, power supply cord, driver software for Windows®, Quick Set-Up Guide (PC interface cable NOT included) The frequency of replacement consumables will vary depending on the complexity of the prints, the percentage of coverage, paper size, page per job, and the type of media.

# Dimensions and Weights

With Carton (WxDxH) 410 x 398.5 x 318.5 mm -11.8kg **Without Carton (WxDxH)** 580 x 517 x 434 mm - 14.7kg

## **Duty Cycles**

Recommended Monthly Up to 2,000 pages monthly print volume **Maximum Monthly**<sup>6</sup> Up to 15,000 pages monthly print volume

All specifications correct at the time of printing and are subject to change.

Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of

their respective companies.

<sup>1</sup> Approx declared yield value in accordance with ISO/IEC 19752.

<sup>2</sup> Calculated with 80g/m² paper.

<sup>3</sup> Windows® & Mac® only.

<sup>4</sup> Windows®only.

<sup>5</sup> Optional download.

<sup>6</sup> Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

<sup>7</sup> Requires Brother software.

### **Environment**

**Power Consumption** 

Printing - 440W (260W in quiet mode), Ready - 42W,

Sleep - 6.2W, Deep sleep -

0.6W, Off - 0.03W

**TEC Value** 

1.232kWh/Week

**Sound Pressure Level** 

Printin g

48dbA, Quiet mode

printing 44dbA, Ready

Up to 30dbA

**Power Saving** 

This enables the printer to consume less energy when not in use

**Toner Saving** 

This reduces the toner usage and helps to reduce the total cost of printer ownership

**Energy Star** 

Yes

**Eco Mode** 

Yes

Fax

Fax Modem

33,600bps (Super G3)

PC Fax Send9&3

Send faxes directly from your

PC

PC Fax Receive984

Receive faxes directly to your

PC

**Fax Forwarding** 

Sends a fax received in memory to another pre-programmed fax number

All specifications correct at the time of printing and are subject to change.

Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of their respective companies.

<sup>1</sup> Approx declared yield value in accordance with ISO/IEC 19752.

<sup>2</sup> Calculated with 80g/m² paper.

<sup>3</sup> Windows® & Mac® only.

<sup>4</sup> Windows®only.

<sup>5</sup> Optional download.

<sup>6</sup> Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

<sup>7</sup> Requires Brother software.