



# Wireless colour LED laser printer

HL-L3230CDW





brother.co.uk/hl-l3230cdw

## Wireless colour LED laser printer

The HL-L3230CDW is the ideal colour printer for users wanting to save time and money. With quick time saving features such as automatic 2-sided printing, and the large 250 sheet paper capacity, this printer is a real asset to any home or office. Also offering both wired and wireless connectivity, with the added benefit of printing on the go from your mobile or tablet device.

HL-L3230CDW



#### **Key features:**

- Fast print speeds of 18 pages per minute (ppm)
- Large paper capacity of 250 sheets
- Automatic 2-sided printing
- Wired and wireless connectivity
- Easily print from your mobile or tablet device
- 256MB memory
- Up to 1,000 pages\* in-box toners.

#### Designed with efficiency in mind

This robust desktop device is easy to use and simple to set up. With the large in-box toners giving you up to 1,000 pages\* straight from the box, your new machine is ready to use straightaway. Combine this with automatic 2-sided printing and quick print options from both your phone and tablet devices, this machine gives you the peace of mind required when running a business.

#### Save time and money

These desktop devices are fast, reliable and great value. The built-in 250 sheet paper capacity allows you to keep working longer without having to replenish the paper tray. By using the high yield supplies, you won't have to spend time changing your toner as often, as well as achieving a competitive cost per page for both colour and mono. By boosting productivity, and reducing any down time, your office can run more smoothly.

#### Don't add to the office noise

Within a busy office environment, you don't need any additional noise to distract you from your work. The HL-L3230CDW prints full colour pages at print speeds of up to 18ppm at under 45dB which is quietest in its class, making it perfect for desktop working.



#### General

#### **Technology**

Electrophotographic

#### Processor

Cortex-A9 800MHz Sub: ARM946 133MHz

#### Memory 256MB

Wired network 10Base-T/100Base-TX

#### Wireless network

IEEE 802.11b/g/n

#### Control panel

1 line LCD

#### Local interface

Hi-Speed USB 2.0

#### Mobile print

Print from your mobile devices to your Brother printer

#### Print

#### Print speed (A4)

18ppm colour and mono

#### Print speed 2-sided (A4)

6 sides per minute colour and mono. Print on to both sides of the paper automatically

#### Resolution

2,400dpi (600 x 2,400)

#### Quiet mode

A mode to reduce the printing noise by reducing the print speed to 12ppm

#### First print out time

Less than 15.5 seconds from ready mode

#### Warm up time

Less than 24 seconds from sleep mode

#### Print languages

PCL6, BR-Script3 PDF Version 1.7, XPS Version 1.0

#### **Embedded fonts (PCL)**

73 scalable fonts, 12 bitmap fonts

#### **Embedded fonts (Postscript)**

66 scalable fonts

#### **Embedded barcodes (PCL)**

\*Code39, Interleaved 2 of 5, FIM (US-PostNet), Post Net (US-PostNet), EAN-8, EAN-13, UPC-A, UPC-E, Codabar, ISBN (EAN), ISBN (UPC-E), Code128 (set A, set B, set C), EAN128 (set A, set B, set C), Code93, GS1Databar, MSI

#### **Printer functions**

#### N-up printing<sup>3</sup>

Reduce up to 2, 4, 9, 16 or 25 A4 pages into just one A4 page (Mac, up to 2, 4, 6, 9, or 16)

#### Poster printing<sup>4</sup>

Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages

#### Watermark printing4

Watermark your documents with predefined text or with your own user-defined messages

#### ID printing4

Add identification to your printed documents (date and time, short custom message or PC username)

#### Manual 2-sided print4

Manual 2-sided printing (recommended for media not supported by automatic 2-sided print)

#### Booklet printing4

Print documents in A5 booklet format using automatic or manual 2-sided print

#### Print profiles<sup>3</sup>

Store your favourite driver settings as profiles to easily recall them

#### Print text in black4

Converts all text in your documents to black when printed

#### **Printer driver**

#### Windows®

Windows® 10 (32 and 64 bit editions) Windows® 8 (32 and 64 bit editions) Windows® 7 (32 and 64 bit editions) Windows® Server 2016 (32 and 64 bit editions)\* Windows® Server 2012, 2012R2 and 2008R2\* Windows® Server 2008 (32 and 64 bit editions)\*

#### Macintosh<sup>5</sup>

macOS v10.11.6, 10.12.x, 10.13.x

#### Linux<sup>5</sup>

CUPS, LPD/LPRng (32 and 64 bit editions)

#### PostScript universal printer driver<sup>5</sup>

Driver for Windows® that enables you to print to any network or locally-connected Brother laser printer that supports PostScript

#### PCL driver<sup>5</sup>

Generic PCL XL driver

\* Windows® Server supports network printing only

All specifications correct at the time of printing (August 2018) and are subject to change. Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of their respective companies.

<sup>1</sup> Approx declared yield value in accordance with ISO/IEC 19798.

<sup>2</sup> Calculated with 80g/m² paper.

<sup>3</sup> Windows® & Mac® only. 4 Windows® only.

<sup>5</sup> Optional download.

<sup>6</sup> Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

#### Paper handling

#### Paper input

Standard tray - 250 sheets Manual feed slot - 1 sheet

#### Paper output

150 sheets face down (80g/m²)
1 sheet face-up (straight paper path)

### Media type and weights standard tray

Plain and recycled paper (between 60 - 163g/m²)

#### Media sizes standard tray

A4, letter, A5, A5 (long edge), A6, executive

### Media type and weights 2-sided print

Plain and recycled paper (between 60 - 163g/m²)

### Media sizes 2-sided print

#### **Envelope and label printing**

Manual feed slot: support for 1 envelope / sheet

### Media type and weights manual feed slot

Plain, recycled, bond, label, envelope paper (between 60 - 163g/m²)

#### Media sizes manual feed slot

Width: 76.2 to 216 mm Length: 116 to 355.6 mm Envelope: COM-10, DL, C5,

Monarch

### Mobile and web connectivity

### Brother iPrint&Scan (Android)

Print from, scan to, send faxes, preview received faxes, preview copies and check the machine status from an Android device

### Brother iPrint&Scan (iPad / iPhone / iPod)

Print from, scan to, send faxes, preview received faxes, preview copies and check the machine status from an iPad / iPhone / iPod Touch

### Brother iPrint&Scan (Windows® Phone)

Print from and scan to a smart phone running the Windows® Phone operating system

### Brother iPrint&Scan (Windows® 8,10 & RT)

Print from and scan to a Windows® 8,10 or Windows RT tablet

#### **Google Cloud Print 2.0**

Print most common file types from any Google Cloud Print enabled application

#### Apple AirPrint

Print from and scan to most common file types from any AirPrint enabled application

#### **Brother Print Service Plugin**

Print from Android devices without a dedicated app

#### Mopria

Print most common file types from Mopria supported Android devices

### Fleet management tools

#### Unattended installer4

Ability to centrally deploy and customise our drivers and software

#### MSI installer4

Modular installers that can be distributed through Active Directory®

#### **BRAdmin Light**<sup>4&5</sup>

LAN/WAN management software

#### Embedded web server

Web based print management software embedded onto the device

#### Driver deployment wizard4

Easily create print drivers for hassle free deployment over your network

#### PrintSmart Cost Control

Monitor and control printing costs for all Brother and 3rd party devices

For more information on PrintSmart Solutions visit: brother.co.uk

#### **Software**

### Brother iPrint&Scan (Windows and Mac)<sup>5</sup>

Print from, scan to, send faxes, preview received faxes, preview copies and check the machine status from Windows, macOS or PC

- 1 Approx declared yield value in accordance with ISO/IEC 19798.
- 2 Calculated with 80g/m² paper.
- 3 Windows® & Mac® only.
- 4 Windows® only.
- 5 Optional download.
- 6 Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

All specifications correct at the time of printing (August 2018) and are subject to change. Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of their respective companies.

#### **Network and security**

#### Wired network

10Base-T/100Base-TX

#### Wired network security

SMTP-AUTH, SSL/TLS (IPPS, HTTPS, SMTP, POP), SNMP v3 802.1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP-TTLS), Kerberos

#### Wireless network

IEEE 802.11b/g/n (infrastructure mode) IEEE 802.11g/n (Wi-Fi Direct)

#### Wireless network security

WEP 64/128 bit, WPA-PSK (TKIP/AES), WPA2-PSK (AES)
\*Wi-Fi Direct supports
WPA2-PSK (AES) only.APOP,
POP before SMTP,
SMTP-AUTH, SSL/TLS (IPPS,
HTTPS, SMTP, POP), SNMP v3
802.1x (LEAP, EAP-FAST,
PEAP, EAP-TLS, EAP-TTLS),
Kerberos

#### Wi-Fi Direct™

Print wirelessly without having to go through a wireless access point (both automatic and manual methods supported)

#### Wireless setup support

Wi-Fi Protected Setup (WPS)

#### Wireless applications

Vertical pairing

#### IPv4

ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, IPP/IPPS, FTP Server, TELNET Server, HTTP/HTTPS server, TFTP client and server, SMTP Client, SNMPv1/v2c/v3, ICMP, Web Services (Print), CIFS client, SNTP client

#### IPv6

NDP, RA, DNS resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, IPP/IPPS, FTP Server, TELNET Server, HTTP/HTTPS server, SMTP Client, SNMPv1/v2c/v3, ICMPv6, Web Services (Print), CIFS Client, SNTP Client

#### **IP** filter

Restrict which network users can or cannot access the device over the network (IPv4 only)

#### E-mail notifications

Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing

#### E-mail reports

Receive usage reports on a regular basis via e-mail

#### **Setting lock**

Secures access to the devices control panel by locking it

#### Secure Function Lock 3.0

Restrict access to individual or groups of users over a network. Can be used with PC user login names for up to 100 users

#### Secure print

Protect print jobs with a four digit release code required at the device in order for them to be printed

### Supplies and accessories

#### In-box toner<sup>1</sup>

1,000 pages BK/C/M/Y

#### Standard yield toner<sup>1</sup>

1,000 pages BK/C/M/Y (TN-243)

#### High yield toner<sup>1</sup>

3,000 pages BK 2,300 pages C/M/Y (TN-247)

#### Drum unit<sup>1</sup>

18,000 pages (1 page / job) (DR-243CL)

#### Belt unit<sup>1</sup>

Approx. 50,000 pages (2 page / job) (BU-223CL)

#### Waste toner box1

Approx. 50,000 pages (5 page / job) (WT-223CL)

### Dimensions and weights

### **With carton (WxDxH)** 589 x 513 x 372 mm 21.5kg

#### Without carton (WxDxH)

410 x 461x 252 mm 18kg

All specifications correct at the time of printing (August 2018) and are subject to change. Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of their respective companies.

<sup>1</sup> Approx declared yield value in accordance with ISO/IEC 19798.

<sup>2</sup> Calculated with 80g/m² paper.

<sup>3</sup> Windows® & Mac® only.

<sup>4</sup> Windows® only.

<sup>5</sup> Optional download

<sup>6</sup> Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

#### **Duty cycles**

#### **Recommended monthly**

300 to 1,500 pages monthly print volume

#### Maximum monthly<sup>6</sup>

Up to 30,000 pages monthly print volume

#### **Environment**

#### **Power consumption**

Printing - 390W Ready - 75W Quiet mode - 270W Sleep - 8.8W Deep sleep - 1.0W Off - 0.04W

#### **TEC** value

0.9 kWh/Week

#### Sound pressure level

Printing - 45dB(A) Ready - 33dB(A) Quiet mode - 43dB(A)

#### Sound power

Printing: 5.93B(A) colour/mono Ready: 4.67B(A)

Quiet mode: 5.86B(A) colour /

5.78B(A) mono Deep sleep: inaudible

#### **Power saving**

This enables the printer to consume less energy when not in use

#### **Toner saving**

This reduces the toner usage and helps to reduce the total cost of printer ownership

#### **Energy Star**

Yes

**GS** mark Yes

Eco mode

Yes

All specifications correct at the time of printing (August 2018) and are subject to change. Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of their respective companies.

<sup>1</sup> Approx declared yield value in accordance with ISO/IEC 19798.

<sup>2</sup> Calculated with 80g/m² paper. 3 Windows® & Mac® only. 4 Windows® only.

<sup>5</sup> Optional download.

<sup>6</sup> Maximum number of printed pages per month can be used to compare designed durability between like Brother products. For maximum printer life, it is best to choose a printer with a duty cycle that far exceeds your print requirements.

















#### Working with you for a better environment

At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call this approach Brother Earth.

www.brotherearth.com

All specifications correct at the time of printing (August 2018) and are subject to change. Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of their respective companies.

