PRODUCT DATASHEET

NiMH Battery Charger (CHVC2)

CONVENIENT Charges 2 or 4 NiMH AA's or AAA's EASY Energizer LED Indicators SLEEK Compact Design **ECONOMICAL** Value Priced **CORDLESS** Fold-out Plug

Value Charger



Before Using Your Charger: Please read all instructions and cautionary markings on the battery charger, batteries, and device.

Best used with Energizer NiMH batteries.

North American Region Download Instructions and Warranty Information

English | Français | Español

Product Detail:



Designation: Value Charger Model: CHVC2 Color: Silver Charge Capability: "AA" (2) or (4) / "AAA" (2) or (4) "AA" (2) and "AAA" (2) Simultaneously Note: When charging only 2 batteries, place batteries in the two positions to the left or right.

Charging Times:	Battery	Capacity	Estimated
(estimated)	(NiMH)	(mAh)	(time)
	AA	1300-2000	8-12.5 hrs
	AA	2100-2500	13-16 hrs
	AAA	850-900	11-12 hrs

 Shutoff Mechanism:
 None

 Charging Current:
 "AA" 190mA

 "AA" 90mA
 "AAA" 90mA

 Trickle Charge:
 None

 Input Rating:
 120VAC, 60Hz

 Input Power:
 6W

 Typical Weight:
 184.3 grams (5.9 oz.)

 Dimensions (mm):
 132 x 70 x 57 (H x L x W)

Rev Polarity Protection: Yes Primary Battery Detection: None

Important Notice

This datasheet contains information specific to products manufactured at the time of its publication. ©Energizer Holdings, Inc. Contents herein do not constitute a warranty.

