### PRODUCT DATASHEET

## NiMH Battery Charger (CH1HR-2)

### **Energizer® 1 Hour Charger**

NIMH BACKER

TATU

# North American Region Download Instructions and Warranty Information

English | Français | Español

#### **EASY**

• Easy to read charge status indicator



#### **FAST**

Charges 4 AA or AAA in about 1 hour



#### **ECONOMICAL**

 Batteries can be charged hundreds of times



#### **Before Using Your Charger:**

1 CHARGER/CHARGEUR & 2AA/2AAA NWH BATTERIES/PILES

Please read all instructions and cautionary markings on the battery charger, batteries, and device.

Best used with Energizer NiMH batteries.

#### **Product Detail:**

Designation: 1 Hour Charger

Color: Silver

Charge Capability: 1 to 4 "AA" / 1 to 4 "AAA"

Charging Time: (estimate)

Battery Capacity Estimated (time)\* (NiMH) (mAh) AA 2450 60 min AA 2000 50 min AAA 1700 42 min AAA 850 52 min

Shutoff Mechanism: Timer 80 min. charge, 12 hr. trickle

Temperature detection at 60°C

Charging Current: "AA" 2.5A max

"AAA" 1.0A max

Trickle Charge: "AA" 50mA

"AAA" 20mA

Input Rating: Universal Voltage: 100-240V AC, 50/60Hz

Input Current: DC 12V-16V, ≈1.3A

Typical Weight: 108 grams (3.8 oz.) w/o adapter Dimensions (mm): 31 x 115 x 75 (H x L x W)
Safety Features: Delta V Charging Cut Off

Short Circuit and Reverse Polarity Protection

Safety Timer to Prevent Over Charge

Bad Battery Detection

\*Per American National Standards Institute (ANSI) Standard

#### **Important Notice**

This datasheet contains information specific to products manufactured at the time of its publication.

© Energizer Holdings, Inc.

Contents herein do not constitute a warranty.

